

Random Scattering Matrices and the Circuit Theory of Andreev Conductances

Nathan Argaman

Institute for Theoretical Physics, University of California, Santa Barbara, CA 93106, USA

(August '96)

Abstract

The conductance of a normal-metal mesoscopic system in proximity to superconducting electrode(s) is calculated. The normal-metal part may have a general geometry, and is described as a “circuit” with “leads” and “junctions”. The junctions are each ascribed a scattering matrix which is averaged over the circular orthogonal ensemble, using recently-developed techniques. The results for the electrical conductance reproduce and extend Nazarov’s circuit theory, thus bridging between the scattering and the bulk approaches. The method is also applied to the heat conductance.

PACS numbers: 74.50.+r, 74.80.Fp, 73.23.Ps

Mesoscopic normal-metal–superconductor (N-S) proximity effects are often described theoretically using the Usadel equations [1] — the partial differential equations of inhomogeneous (dirty) superconductivity. However, the ohmic resistance of the normal-metal part of the structure [2] can also be found from the “circuit theory of Andreev conductance” — a set of algebraic relations recently derived from the Usadel equations by Yuli Nazarov [3] (the Usadel equations themselves are derived from the Eilenberger equations of clean superconductors, which ultimately derive from the Keldysh technique). Here we pursue an alternative approach, which associates a random scattering matrix with each of the junctions in the “circuit”. These matrices are to be averaged over one of the circular ensembles of random matrix theory, employing diagrammatic techniques which were developed specifically for such purposes [4,5].

Electron and hole excitations can enter the normal-metal part of such N-S structures (the “circuit”) from one of the normal electrodes (N), but at low excitation energies they can not enter into the superconducting electrodes (S) because of the gap. Instead, Andreev reflections may occur — an electron may evolve into a Cooper pair in S, leaving behind a hole in the Fermi sea of the normal-metal part [6], with a wavevector related to that of the impinging electron by time-reversal. We will assume for simplicity, as did Nazarov [3], that the applied voltages and the ambient temperatures are very small, so that the energy dependence of the scattering properties of the structure can be neglected, and the quantum mechanical propagation is fully coherent. We also assume the absence of a magnetic field (except for Aharonov-Bohm phases), the absence of electron-electron interactions in the normal part of the structure, and unbroken time-reversal symmetry and spin degeneracy.

Unaveraged quantum mechanical transport in a wide variety of structures may be described [7] using two unitary matrices: G_0 represents the “non-local” transport in the “leads”, and S represents random scattering within each of the “junctions”, as well as Andreev scattering at the external superconducting electrodes. We denote the number of internal junctions in the system by K , and the number of junctions and external electrodes by M (we have at least one N and one S electrode, so $M \geq K + 2$; see Fig. 1a). The

number of transverse modes in the lead connecting junctions k and m is denoted by $W_{k,m}$, so that $N_k = \sum_m W_{k,m}$ is the size of the scattering matrix of the k th junction. The N_k s and the (nonzero) $W_{k,m}$ s are treated as large parameters, and the conductances are evaluated to leading order — weak localization and conductance fluctuation corrections will not be considered here. The matrices G_0 and S are of size $2N_{\text{tot}} \times 2N_{\text{tot}}$, where $N_{\text{tot}} = \sum_{m=1}^M N_m$ is the total number of modes, and the factor of 2 represents the electron-hole subspace. G_0 is non-diagonal in the $M \times M$ block structure, but diagonal in the electron-hole space. S is block-diagonal, with K diagonal blocks consisting of a random scattering matrix for the electron-electron sub-block, and the complex conjugate of that matrix for the hole-hole sub-block. The remaining diagonal blocks of S either vanish, for an external normal electrode, or are off-diagonal in the electron-hole space: the electron-hole Andreev-scattering sub-block for a superconducting electrode m is equal to $i \exp(-i\chi_m)$ (times a unit $N_m \times N_m$ matrix), and the hole-electron sub-block is $i \exp(i\chi_m)$. Here the χ_m s are the given, time-independent phases of the superconducting order parameter in m . The extra factors of i lead to *destructive* interference after two consecutive Andreev scatterings, and are responsible for, e.g., proximity-induced gap-like features in the normal part of the structure.

We now average the K random-scattering diagonal blocks of S over the appropriate matrix ensemble — the circular orthogonal ensemble (COE), justifying our expressions both physically and technically (see Ref. [4] for details of the latter). Diagrams for the conductance may be drawn as in Fig. 1b, with matrix multiplication implied along the bottom and the top of the diagram. The matrices along the top line are hermitean conjugated, so that the diagrams represent probabilities, or amplitudes multiplied by complex conjugates of amplitudes. Averaging is evaluated to leading order by connecting the random elements of S , represented as double lines, in all possible ways in the plane of the diagram without crossing lines. These connections or couplings (Fig. 1c) join together n occurrences of the k th random scattering matrix and n occurrences of its hermitean (or complex) conjugate, in alternating order; the corresponding weights are $(-1)^{n-1} c_n / N_k^{2n-1}$ with $c_n = (2n)! / 2(2n-1)(n!)^2$ (these are deduced in Refs. [4] and [5] from unitarity). Each $2n$ -fold coupling divides the plane of

the diagram into $2n$ regions, with matrix multiplication performed independently around the periphery of each region. The blocks of S which are not averaged over — those representing Andreev scattering at the superconducting electrodes — are drawn as black semicircles.

The averaged propagator $G = \langle G_0 + G_0 S G_0 + \dots \rangle$ is written as $G = G_0 / (I - \Sigma G_0)$, where the “one particle irreducible part”, or “self-energy” Σ represents the “average” scattering by the junctions (Fig. 1d). The structure of Σ is particularly simple, because (a) both normal scattering and off-diagonal (in mode space) electron-hole scattering average to zero due to the random phases involved, and (b) the diagonal electron-hole scattering elements of Σ must be equal to each other within each of the K random-scattering blocks, due to ergodicity in each junction. We denote the electron-hole averaged Andreev scattering amplitude by if_k , where f_k is a complex number in the unit circle. The hole-electron amplitude is then if_k^* . Direct Andreev scattering (black semicircles) is also conveniently included in Σ : for the superconducting electrodes $f_m = \exp(-i\chi_m)$, and for the normal ones $f_m = 0$.

The behavior of the amplitudes f_k is similar to that of voltages — if a certain junction is connected by a lead with a high conductance to an electrode with a given value of f_m , then the value of f_k in that junction will tend towards f_m . These amplitudes are physically observable in the following sense: if we were to inject electrons directly into the k th junction from an additional normal electrode which is relatively weakly coupled to that junction — a “noninvasive voltage probe” — we would find a strong beam of holes being retro-reflected into that voltage probe, with an intensity of $|f_k|^2$ times that of the electron beam. The fact that these amplitudes are of order 1, rather than of order $1/N_k$, has been referred to in the literature as the “giant (Andreev) backscattering peak” [8]. It can be understood on the basis of the analogy between Andreev reflections and phase-conjugating mirrors in optics.

For the specific case of ideal leads, $G = G_0 + G_0 \Sigma G_0 + \dots$ is a simple sum over multiple Andreev reflections. For example, $G_{kh,j;ke,j}^m = if_m + if_m if_k^* if_m + \dots = if_m / (1 + f_m f_k^*)$, where j is the index of one of the $W_{k,m}$ modes in the lead connecting k and m (the superscript m has been added to emphasize this; kh and ke denote the k th diagonal electron-hole sub-block). On the other hand, the diagrams for Σ express f_k as a sum of powers of α_k and α_k^* ,

where $i\alpha_k = (1/N_k) \sum_{j=1}^{N_k} G_{kh,j;ke,j}$ is a trace of a sub-block of G . When the explicit values of the c_n s are used and the relationship between α_k and f_k is inverted, it reads simply

$$\frac{f_k}{1 + |f_k|^2} = \alpha_k = \frac{1}{N_k} \sum_m W_{k,m} \frac{f_m}{1 + f_m f_k^*} . \quad (1)$$

This is consistent with the physical requirement that $f_k = f_m$ if all the f_m s in the sum are equal to each other. Eq. (1) may be rewritten, using $\sum_m W_{k,m} = N_k$, as an expression of “spectral current conservation”:

$$\sum_m J_{k,m} = 0 \quad ; \quad J_{k,m} = 2 \sum_{j=1}^{W_{k,m}} \left((1 + |f_k|^2) G_{kh,j;ke,j}^m - f_k \right) = W_{k,m} 2 \frac{f_m - f_k}{1 + f_m f_k^*} , \quad (2)$$

where $J_{k,m}$ denotes the dimensionless (complex) “spectral current” in the (k, m) lead.

The “two-particle irreducible vertex”, Γ is represented diagrammatically in Fig. 1e. It is also block-diagonal, with all of the elements of the k th block given by $\frac{1+|f_k|^2}{N_k(1-|f_k|^2)} \begin{pmatrix} 1 & -|f_k|^2 \\ -|f_k|^2 & 1 \end{pmatrix}$ (each of the four sub-blocks are full matrices with identical elements). This expression is the only one consistent with unitarity or current conservation [9]. The two-particle propagator, or “diffuson” is given by $D = \Gamma + \Gamma t \Gamma + \dots$, where the elements of t are equal to the absolute squares of the corresponding elements of G . Rather than evaluating the matrix D directly, as would be necessary in order to express the conductances in the usual scattering approach [7,10], we define occupation probabilities v for the electron and hole modes leaving any of the junctions or electrodes. For example, $v_{me(h),j}(\epsilon) = 1 / \left(1 + \exp[(\epsilon \pm eV_m)/k_B T_m] \right)$ for an external normal electrode m with an applied voltage V_m and a temperature T_m (here ϵ is the excitation energy relative to the Fermi surface of the superconducting electrodes). The values of v for modes leaving internal junctions of the circuit are given by $v = \Gamma t v$, where the probabilities v on the right hand side represent the neighbouring junctions or electrodes, and the factors of t and Γ represent transport into and inside the junction, respectively. It is convenient to rewrite this as

$$D^{-1}v = (\Gamma^{-1} - t)v = 0 , \quad (3)$$

with the equality required only for the K internal junctions.

As we assume that no inelastic processes occur in the structure, the electric current I and the quasiparticle current Q are conserved differentially at each junction k :

$$\sum_m I_{k,m}(\epsilon) = 0 \quad ; \quad \sum_m Q_{k,m}(\epsilon) = 0 . \quad (4)$$

The total electric current, $I_{k,m} = \int_0^\infty d\epsilon I_{k,m}(\epsilon)$, and heat current, $Q_{k,m} = \int_0^\infty \epsilon d\epsilon Q_{k,m}(\epsilon)$, are consequently conserved as well. For ideal leads, Eq. (3) implies that [9]

$$I_{k,m} = \frac{2e^2}{h} W_{k,m} \frac{(1 + |f_m|^2)(1 + |f_k|^2)}{|1 + f_m f_k^*|^2} (V_k - V_m) ; \quad (5)$$

$$Q_{k,m} = \frac{2}{h} W_{k,m} \frac{(1 - |f_m|^2)(1 - |f_k|^2)}{|1 + f_m f_k^*|^2} (U_k - U_m) , \quad (6)$$

where the voltages V_m and the excitation-energy densities U_m are defined by [11]

$$V_m = \frac{1}{e} \int_0^\infty d\epsilon \frac{v_{hm} - v_{em}}{1 + |f_m|^2} \quad ; \quad U_m = \int_0^\infty d\epsilon \epsilon \frac{v_{hm} + v_{em}}{1 - |f_m|^2} . \quad (7)$$

These definitions are reasonable because $|f_m| = 0$ at the N electrodes. At the S electrodes, both the voltages V_m and the heat currents $Q_{k,m}$ vanish. The net heat current into an external normal electrode m is $Q_{k,m} - I_{k,m} V_m$ and not just $Q_{k,m}$, because of the shift in the Fermi level. This completes the derivation for ideal leads — the conservation of the currents of Eqs. (2), (5) and (6) at each junction determines the Andreev amplitudes f_k , the voltages V_k and the energy densities U_k self-consistently. Although seemingly local, this scheme takes into account the long-range proximity effects. Aharonov-Bohm effects can also be included simply by gauging out the vector potential $\mathbf{A}$ separately along each lead, i.e. by multiplying each occurrence of f_m in the equations by $\exp(i2e \int_m^k \mathbf{A} \cdot d\mathbf{x} / \hbar)$.

Electronic transport in a non-ideal (k, m) lead may be described by an arbitrary (but non-random) scattering matrix. Using the polar decomposition of this matrix, and the symmetry of the COE, the transmission and reflection eigenvectors can be absorbed into the scattering of the k and m junctions (assuming that time-reversal symmetry is preserved). This means that without loss of generality we may associate a transmission probability T_j with each of the $W_{k,m}$ modes in the lead. The corresponding transmission and reflection amplitudes in G_0 are equal to $i\sqrt{T_j}$ and $\sqrt{1 - T_j}$ respectively. Expressing $G = G_0 + G_0 \Sigma G_0 + \dots$ in terms

of the T_j s, f_k and f_m involves only inverting a j -dependent 2×2 matrix [the electron-hole structure is simplified by separating the even (Andreev reflecting) terms in the sum from the odd (non-Andreev) terms]. With the notation $\beta_{k,m} = (f_m - f_k)/(1 + f_m f_k^*)$, the spectral current becomes

$$J_{k,m} = 2 \sum_{j=1}^{W_{k,m}} T_j \beta_{k,m} \left(1 + (1 - T_j) |\beta_{k,m}|^2\right)^{-1}. \quad (8)$$

Expressions for charge and heat transport are similarly obtained, by replacing the factor $W_{k,m}/|1 + f_m f_k^*|^2$ in Eqs. (5) and (6) with $\sum_{j=1}^{W_{k,m}} (t_{ke,j;me,j} \mp t_{kh,j;me,j})$ (the minus sign is used for charge currents). This can be generalized to any form of G_0 , and so not only non-ideal leads but arbitrary combinations of random and non-random scattering can be treated (the simplification due to the polar decomposition does not easily generalize, however).

The results are summarized in Table 1, using Nazarov's notation. $g_{k,m} = \sum_{j=1}^{W_{k,m}} T_j$ denotes the dimensionless conductance of the lead, in the absence of proximity effects. The Andreev amplitudes f_k are related to Nazarov's "spectral vectors" $\hat{s}_k$ by a stereographic projection from the complex unit disc onto the upper hemisphere: $f_k = \tan(\vartheta_k/2) \exp(i\varphi_k)$ where ϑ_k and φ_k are the polar and azimuthal angle of $\hat{s}_k$. The angle difference $\Delta\theta_{k,m}$ is the "distance" between $\hat{s}_k$ and $\hat{s}_m$ on the sphere, given by $\hat{s}_k \cdot \hat{s}_m = \cos(\Delta\theta_{k,m})$, or $\tan(\Delta\theta_{k,m}/2) = |\beta_{k,m}|$. In the last two lines of the table, we specialize the general expressions to the cases treated in Ref. [3] — diffusive leads and leads containing strong tunnel barriers ($T_j \rightarrow 0$) — reproducing the older results. The complex phases of the $J_{k,m}$ s are also simply related to the directions of the spectral currents in Nazarov's picture, given by $\hat{s}_k \times \hat{s}_m$.

The results for (the electrical conductance of) diffusive leads can be obtained by two different methods: First, by integrating over the known distribution of transmission eigenvalues in such leads [12], one finds that the enhancement of electrical conductance by Andreev reflections in relatively open channels ($T_j \rightarrow 1$) is exactly counterbalanced by the inhibition of "Cooper-pair tunneling" in relatively closed channels ($T_j \rightarrow 0$), regardless of the value of $\Delta\theta_{k,m}$; Second, by treating the diffusive lead as $L \gg 1$ ideal (or tunnel) leads connected in series through $L - 1$ additional junctions, one finds that the spectral vectors of the in-

intermediate junctions lie on the big arc that connects $\hat{s}_k$ and $\hat{s}_m$ with angle differences of $\Delta\theta_{k,m}/L$, resulting in very small proximity induced corrections to electrical conductivity (L occurrences of a quantity which is quadratic in $\Delta\theta_{k,m}/L$). Thus, electrical conductance in diffusive leads is unchanged by the proximity effects being considered (see Fig. 2b below).

Motivated in part by the “Andreev interferometer” experiment of Petrashov *et al.* [13], we plot in Fig. 2 the electric and heat conductances of three structures of a geometry shown in the inset: one with ideal leads, one with diffusive leads, and one with tunnel barriers (each structure has 8 identical leads). The results are obtained numerically by repeatedly shifting each of the f_k s in the complex plane by a fraction of the mismatch in the spectral current, $\sum_m J_{k,m}$, until the iterations converge. An applied magnetic field leads to fast oscillations due to the induced phase-difference between the two superconducting electrodes, and slow oscillations (only one period shown) due to the Aharonov Bohm flux threaded through a small ring in the structure. The results exhibit some similarities to the experimental data, but as stated above, we are unable to reproduce the experimental oscillations (of the order of 10%) of the electrical resistance in a diffusive system. As pointed out in Ref. [14], these may be due to the finite temperature involved (20 mK), requiring a generalization of the present analysis.

In summary, using diagrammatic techniques of random scattering-matrix theory, we have rederived and enhanced Nazarov’s circuit theory of Andreev conductance. The results follow in fact quite simply from notions of multiple Andreev scattering, which is taken to occur locally in the k th junction with an amplitude f_k (this is the amplitude of the “giant Andreev backscattering peak” [8]). The values of f_k are found self-consistently in a manner analogous to finding the voltages in the junctions of an electrical circuit. Heat transport was also briefly considered here, whereas the extension to finite temperatures and voltages is an important goal for future developments.

I would like to thank C.W.J. Beenakker, P.W. Brouwer, B. Spivak and A. Zee for numerous discussions. Financial support of a Fulbright fellowship and NSF grants No. PHY94-07194 and No. DMR93-08011 is acknowledged.

REFERENCES

- [1] K. Usadel, Phys. Rev. Lett. **25**, 507 (1970).
- [2] For a review, see C.W.J. Beenakker, in *Mesoscopic Quantum Physics* (Les Houches Session LXI), edited by E. Akkermans *et al.* (Amsterdam, Elsevier, 1995).
- [3] Yu.V. Nazarov, Phys. Rev. Lett. **73**, 1420 (1994); T.H. Stoof and Yu.V. Nazarov, Phys. Rev. B **54**, 772R (1996); See also: Yu.V. Nazarov, Phys. Rev. Lett. **73**, 134 (1994); Report No. cond-mat/9410011.
- [4] N. Argaman and A. Zee, cond-mat/9603136, Phys. Rev. B (in press). Note that there the direct Andreev reflections (black semicircles) were included in G_0 , not in S and Σ .
- [5] P.W. Brouwer and C.W.J. Beenakker, cond-mat/9604059, J. Math. Phys. (in press); (notice esp. Sec. 6C there).
- [6] A.F. Andreev, Zh. Eksp. Theor. Fiz. **46**, 1823 (1964) [Sov. Phys. JETP **19**, 1228 (1964)].
- [7] C.W.J. Beenakker, Phys. Rev. B **46**, 12 841 (1992).
- [8] C.W.J. Beenakker, J.A. Melsen, P.W. Brouwer, Phys. Rev. B **51**, 13883 (1995).
- [9] The conductances can be derived solely from the block off-diagonal terms in Eq. (3). The consistency with the diagonal terms (i.e. current conservation in the leads) relies on the vanishing of $f_k^* \sum_m J_{k,m} + \text{c.c.}$. By reversing the argument one may derive the expression for Γ , or prove that the component of $J_{k,m}$ parallel to f_k is conserved.
- [10] C.J. Lambert, V.C. Hui and S.J. Robinson, J. Phys. Condens. Matter **5**, 4187 (1993).
- [11] The voltages V_m here are the electro-chemical potentials of the quasiparticles; the electrostatic potentials are obtained by appropriately weighting this with the (vanishing) electro-chemical potential of the superconducting component (see Ref. [14] below).
- [12] For a wide, diffusive wire, $\sum_j F(T_j) \simeq g \int_0^\infty dx F(\cosh^{-2} x)$ for a general function F ;

- O.N. Dorokhov, Solid State Comm. **51**, 381 (1984). Our integrations may be simplified considerably by a change of variables from x to θ , where $\tan(\theta/2) = \tanh(x) \tan(\Delta\theta/2)$.
- [13] V.T. Petrashov, V.N. Antonov, P. Delsing, and T. Claeson, Phys. Rev. Lett. **74**, 5268 (1995); Pis'ma Zh. Eksp. Theor. Fiz. **60**, 589 (1994) [JETP Lett. **60**, 606 (1994)].
- [14] Yu.V. Nazarov and T.H. Stoof Phys. Rev. Lett. **76**, 823 (1996); T.H. Stoof, and Yu.V. Nazarov, Phys. Rev. B **53**, 14496 (1996).

TABLE

type of lead	spectral current	electrical conductance	heat conductance
ideal ($T_j = 1$)	$W_{k,m} 2 \tan \frac{1}{2} \Delta \theta_{k,m}$	$W_{k,m} \cos^{-2} \frac{1}{2} \Delta \theta_{k,m}$	$W_{k,m} \frac{\cos \vartheta_k \cos \vartheta_m}{\cos^2 \frac{1}{2} \Delta \theta_{k,m}}$
general	$\sum_j \frac{T_j \sin \Delta \theta_{k,m}}{1 - T_j \sin^2 \frac{1}{2} \Delta \theta_{k,m}}$	$\sum_j T_j \frac{\cos \Delta \theta_{k,m} + T_j \sin^2 \frac{1}{2} \Delta \theta_{k,m}}{(1 - T_j \sin^2 \frac{1}{2} \Delta \theta_{k,m})^2}$	$\sum_j \frac{T_j \cos \vartheta_k \cos \vartheta_m}{1 - T_j \sin^2 \frac{1}{2} \Delta \theta_{k,m}}$
tunneling ($T_j \rightarrow 0$)	$g_{k,m} \sin \Delta \theta_{k,m}$	$g_{k,m} \cos \Delta \theta_{k,m}$	$g_{k,m} \cos \vartheta_k \cos \vartheta_m$
diffusive	$g_{k,m} \Delta \theta_{k,m}$	$g_{k,m}$	$g_{k,m} \frac{\cos \vartheta_k \cos \vartheta_m \Delta \theta_{k,m}}{\sin \Delta \theta_{k,m}}$

Table 1: The dimensionless spectral current, $|J_{k,m}|$, and electric and thermal conductances, $I_{k,m}/(V_m - V_k)$ and $Q_{k,m}/(U_m - U_k)$, for various types of leads.

FIGURES




Fig. 1: Random-scattering-matrix diagrams for Andreev circuit theory (following Ref. [4]).

a) Schematic drawing of a circuit with $K = 3$ junctions, and six external electrodes ($M = 9$), two of which are superconducting. b) Typical conductance diagram, before averaging; single light lines represent “deterministic” transport in the leads (G_0), dangling double lines represent “random” scattering in the junctions, and full semicircles represent Andreev scattering at the superconducting electrodes. c) Couplings used to join the dangling lines upon averaging, and their weights. d) Diagrams for the “one-particle irreducible part” Σ , and averaged propagator G (thick line). e) Diagrams for the “two-particle irreducible part”, Γ , and the “diffuson” D .




Fig. 2: Overall electrical and heat resistances between the two normal (N) electrodes of the circuit shown in the inset, as a function of magnetic field, in units of the resistance of a single lead (resistance in the absence of proximity effects = 3). a) Ideal leads; b) diffusive leads; c) leads with tunnel barriers. The area enclosed by the normal loop (thin circle) is some 30 times smaller than that of the superconducting loop (thick line in inset).